

jc595 U.S. PTO  
07/07/99

Patent  
Attorney's Docket No. 040070-244

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

UTILITY PATENT  
APPLICATION TRANSMITTAL LETTER

jc135 U.S. PTO  
09/30/99  
07/07/99

Box PATENT APPLICATION  
Assistant Commissioner for Patents  
Washington, D.C. 20231

Sir:

Enclosed for filing is the utility patent application of Kjell Gustafsson, Torsten Carlsson and Torgny Palenius for CONTROLLED ANTENNA DIVERSITY.

Also enclosed are:

- ☒ 4 sheet(s) of ☐ formal ☒ informal drawing(s);
- ☐ a claim for foreign priority under 35 U.S.C. §§ 119 and/or 365 is ☐ hereby made to ☐ filed in ☐ on ☐;  
☐ in the declaration;
- ☐ a certified copy of the priority document;
- ☐ a Constructive Petition for Extensions of Time;
- ☐ ☐ statement(s) claiming small entity status;
- ☒ an Assignment document;
- ☐ an Information Disclosure Statement; and
- ☐ Other: \_\_\_\_\_.

The declaration of the inventor(s) ☒ also is enclosed ☐ will follow.

- ☐ Please amend the specification by inserting before the first line the sentence --This application claims priority under 35 U.S.C. §§119 and/or 365 to ☐ filed in ☐ on ☐; the entire content of which is hereby incorporated by reference.--

The filing fee has been calculated as follows [ ] and in accordance with the enclosed preliminary amendment:

CLAIMS					
	NO. OF CLAIMS		EXTRA CLAIMS	RATE	FEE
Basic Application Fee					\$760.00
Total Claims	20	MINUS 20 =	0	x \$18.00	-0-
Independent Claims	2	MINUS 3 =	0	x \$78.00	-0-
If multiple dependent claims are presented, add \$260.00					-0-
Total Application Fee					\$760.00
If verified Statement claiming small entity status is enclosed, subtract 50% of Total Application Fee					-0-
Add Assignment Recording Fee of \$40.00 if Assignment document is enclosed					40.00
<b>TOTAL APPLICATION FEE DUE</b>					<b>\$800.00</b>

[X] A check in the amount of \$ 800.00 is enclosed for the fee due.

[ ] Charge \$ \_\_\_\_\_ to Deposit Account No. 02-4800 for the fee due.

Please address all correspondence concerning the present application to:

Ronald L. Grudziecki  
Burns, Doane, Swecker & Mathis, L.L.P.  
P.O. Box 1404  
Alexandria, Virginia 22313-1404.


The Commissioner is hereby authorized to charge any appropriate fees under 37 C.F.R. §§ 1.16, 1.17 and 1.21 that may be required by this paper, and to credit any overpayment, to Deposit Account No. 02-4800. This paper is submitted in triplicate.

Respectfully submitted,

BURNS, DOANE, SWECKER & MATHIS, L.L.P.

Date: July 7, 1999

By:

  
Charles F. Wieland III  
Registration No. 33,096

P.O. Box 1404  
Alexandria, Virginia 22313-1404  
(703) 836-6620

## CONTROLLED ANTENNA DIVERSITY

### Background

#### 1) Field of the Invention.

The present invention pertains to systems and methods involved in radio  
5 communication systems and, more particularly, to a system and method for  
controlling antenna diversity.

#### 2) Discussion of Related Art

The cellular telephone industry has made phenomenal strides in  
commercial operations in the United States as well as the rest of the world.  
10 Growth in major metropolitan areas has far exceeded expectations and is rapidly  
outstripping system capacity. If this trend continues, the effects of this industry's  
growth will soon reach even the smallest markets. Innovative solutions are  
required to meet these increasing capacity needs as well as maintain high quality  
service and avoid rising prices.

15 Figure 1 illustrates an example of a conventional cellular radio  
communication system 100. The radio communication system 100 includes a  
plurality of radio base stations 170a-n connected to a plurality of corresponding  
antennas 130a-n. The radio base stations 170a-n in conjunction with the antennas  
130a-n communicate with a plurality of mobile terminals (e.g. terminals 120a,  
20 120b and 120m) within a plurality of cells 110a-n. Communication from a base  
station to a mobile terminal is referred to as the downlink, whereas  
communication from a mobile terminal to the base station is referred to as the  
uplink.

The base stations are connected to a mobile telephone switching office  
25 (MSC) 150. Among other tasks, the MSC 150 coordinates the activities of the  
base stations, such as during the handoff of a mobile terminal from one cell to

another. The MSC 150, in turn, can be connected to a public switched telephone network 160, which services various communication devices 180a, 180b and 180c.

A common problem which occurs in cellular radio communication systems is the loss of information in the uplink and downlink signals as a result of multi-path fading. Multi-path fading occurs when the transmitted signal travels along several paths between the base station and the intended receiver. When the differences in the path lengths between the base station and the mobile terminal are relatively small, the multiple signal images arrive at almost the same time. The images add either constructively or destructively, giving rise to fading, which can have a Rayleigh distribution. When the path lengths are relatively large, the transmission medium is considered time dispersive, and the added images can be viewed as echoes of the transmitted signal, giving rise to intersymbol interference (ISI).

Fading can be mitigated by using multiple receive antennas and employing some form of diversity combining, such as selective combining, equal gain combining, or maximal-ratio combining. Diversity takes advantage of the fact that the fading on the different antennas is not the same, so that when one antenna has a faded signal, chances are the other antenna does not. ISI multi-path time dispersion can be mitigated by some form of equalization, such as linear equalization, decision feedback equalization, or maximum likelihood sequence estimation (MLSE).

Interference can also degrade the signals transmitted between a base station and mobile terminals. For instance, a desired communication channel between a base station and a mobile terminal in a given cell can be degraded by the transmissions of other mobile terminals within the given cell or within neighboring cells. Other base stations or RF-propagating entities operating in the same frequency band can also create interference (e.g., through "co-channel" or "adjacent channel" interference in systems).

Frequency re-use can be used to, among other things, mitigate interference by placing interfering cells as far from each other as possible. Power control can also be used to reduce the interference by ensuring that transmitters communicate at minimal effective levels of power. Such power control techniques are especially prevalent in code-division multiple access (CDMA) systems, due to the reception of information in a single frequency channel at each base station.

The performance of individual radio links as well as the overall system is improved by antenna diversity in the mobile station and/or base station receiver. Having multiple antennas, and processing the information accordingly, helps combat fading and makes the communication link more robust. The price of introducing antenna diversity is the extra radio and base band processing resulting from having more than one signal to demodulate. This price in a mobile station has often been judged to be too large in terms of the increased space, manufacturing costs, and power consumption due to the extra components required.

Currently, one cellular system uses antenna diversity in the mobile station. Specifically, in the Japanese system PDC this form of diversity is normally limited to a version called "selection" diversity. In this case, as shown in Figure 2, one antenna is used at a time. In Figure 2, a first antenna 210 and a second antenna 212 each receive radio signals, including the radio signals from the same source but perhaps different paths. One of the two received radio signals is selected by a selection switch 220 for input to a Radio Frequency (RF) processor 230. The RF processor 230 down converts the received signal and performs other processing before the processed signal reaches a base-band processor 240. The base band processor 240 controls the operation of the RF processor 230. The base band processor 240 also provides a control signal to the selection switch 220 for controlling which antenna signal to process based on criterion such as measured signal strength. This selection as to which antenna used is based on criteria such

as, for example, a measurement of the receive signal strength just before receive slot in a TDMA system.

On one hand, this version of antenna diversity does not fully exploit all that can be gained from the performance of combining signals from these two  
5 antennas. On the other hand, it avoids the cost in terms of extra components and power consumption, resulting from full processing of both antenna signals.

In International Patent Application WO 95/11552, a diversity receiver having two receiver branches is shown. A control signal based on comparison between signal strengths of the received signals is generated. Switching means are  
10 arranged to change-over a signal from either one of the receiver branches to a receiver output in dependence of the control signal. Hence, this is an example of a "selective" diversity system.

In European Patent Application 0,454,585, a diversity selection system switches between diversity antennas for every assigned time slot in a TDMA  
15 system to provide better signal quality according to a prediction algorithm. Hence, this patent is yet another example of a selective diversity system.

New systems for example IMT 2000 are being defined in a way where diversity is more or less necessary to meet some of the specific performance requirements. The overall criteria is to meet some kind of performance measure  
20 for the communication link. This can be monitored in any one of several ways. For example, one can measure the signal-to-noise ratio (SNR) of the received signal, one can measure or estimate a bit error rate (BER) or frame error rate (FER), or one can keep track of the number of required re-transmissions in cases where the radio link protocol uses re-transmissions. In most cases, this will  
25 require more complete implementation of diversity than selection diversity currently offers. Specifically, both antenna signals will need to be fully processed and the process signals combined in the most beneficial manner.

Figure 3 is an example of such a system. In Figure 3, a first antenna 310 receives radio signals and provides its received signals to a first RF processor 330. A second antenna 312 receives radio signals and provides its received signals to a second RF processor 332. The first RF processor 330 processes, e.g., down  
5 converts, the received RF signal to an intermediate signal for input to a base band processor 340. The first RF processor 330 also processes signals to be transmitted, including up converting the signal to a radio frequency for transmission over the first antenna 330.

Simultaneous with the processing of the first RF signal in the first RF  
10 processor 330, the second antenna 312 receives the same signal from the same source, but perhaps over a different radio path. This second signal is processed (e.g., down converted) in the second RF processor 332. The second signal is processed in the second signal processor 332 before being forwarded to the base band processor 340. The second RF processor 332 operates only in a receive  
15 mode.

The need for a lot of extra processing when using diversity is particularly true for systems based on CDMA, since in this case the antenna signal has to pass through most of the base band processing before the quality thereof can be judged. Simple measurements like signal strength do not give enough information about  
20 one individual user signal.

Although antenna diversity may be needed in some situations, there will be other cases where the radio environment allows perfectly adequate performance without diversity. If diversity is implemented such as shown in Figure 3, the mobile station ends up spending power on the diversity processing whether  
25 necessary or not. This leads to shorter operating time for battery operated devices that could have been achieved without the power consumption in the diversity chain.

### Summary and Objects of the Invention

The present inventors have reduced the power penalty of introducing diversity in the mobile station by using the diversity branch only when needed. Figure 4 depicts a solution where the diversity branch can be controlled (i.e.,  
5 switched on or off) by the base band processing circuitry. In this way, it can be decided when the performance gain from using diversity outweighs the extra power consumption and then switch to the diversity processing only in the latter situation.

The criteria for when to use the diversity branch can be both global in the  
10 sense of it being system wide and/or local. In the global case the network evaluates the load on different cells and the network signals the mobile stations when the mobile stations are allowed to switch off the diversity processing. Some of the performance loss is then compensated by increasing the transmit power on the down link to the mobile station, in one embodiment of the present invention.  
15 More specifically, power will likely increase to reach a target Signal to Interference Ratio (SIR) in one loop, and possibly a target SIR will be adjusted based perceived quality in an outer loop.

In the local case, the mobile station itself decides when it wants to use diversity. This decision can be based on current radio performance, the type of  
20 services currently used and/or the remaining battery power, for example.

When not using diversity, the mobile station generally needs a higher SIR (Signal to Interface ratio) to be reached. Whether this request is granted or not depends on the current load in the system. There will be cases when the power cannot be increased and the mobile may be forced to renegotiate the currently used  
25 services (data rates, packet length, etc.) in order to handle the reduced SIR when switching off the diversity processing.

### Brief Description of the Drawings



The foregoing objects, features and advantages of the present invention, as well as other features, will be more clearly understood upon reading the following detailed description in conjunction with the drawings in which:

Figure 1 shows a conventional radio communication system including  
5 plural base stations and a mobile telephone switching office;

Figure 2 shows a conventional selection diversity communication system using a criteria such as the measured signal strength to decide which antenna signal to process;

Figure 3 shows a conventional mobile station having diversity with  
10 complete processing in both received signals;

Figure 4 is an example of the present invention of a receiver with an antenna diversity where the diversity processing is controlled from the base band processing and is turned on when the performance gain justifies the extra power consumption;

Figure 5 is a flow chart showing the operation of a control portion of the  
15 base band processor shown in Fig. 4; and

Figure 6 is a flow chart showing the operation of a different embodiment of a control portion of the base band processor.

#### Detailed Description

20 In the following description, for purposes of explanation and not limitation, specific details are set forth such as particular circuit components, techniques, etc. in order to provide a thorough understanding of the present invention. However, it will be apparent to one skilled in the art that the present invention may be practiced in other embodiments that depart from the specific details. In other  
25 instances detailed descriptions of known methods, devices and circuits are omitted so as not to obscure the description of the present invention.

Figure 4 is a block diagram of a portion of a cellular telephone mobile or base which includes a first antenna 410 and a second antenna 412. The first antenna 410 receives a radio signal for input to a first Radio Frequency (RF) processor 420. The radio frequency processor 420 processes the received RF signals such as down converting the RF signal into a base band received radio signal. While only two antennas and processors are shown, more than two could be employed using the teachings of the present inventors as presented herein. The converted, base band radio signal processed by the RF processor 420 is input to a base band processor 430 for further processing in accordance with CDMA, TDMA, FDMA or other access systems.

Further, the RF processor 420 receives baseband signals from the base band processor 430 for up conversion into radio frequencies to be transmitted over the first antenna 410.

Radio signals are also received on the second antenna 412. This second antenna 412 may receive the same signals originating from the same signal source, but perhaps via a different signal path.

The received signals from the second antenna 412 are input to a second RF processor 422 for radio frequency processing such as down conversion into a base band signal. The down converted base band signal processed by the RF processor 422 is then input to a base band processing circuit 430. The second radio frequency processor 422 is not used in the transmission mode.

The base band processor 430 may be any suitable circuitry for processing base band radio frequencies and is envisioned to be in the form of an application specific integrated circuit (ASIC). Naturally, any type of base band processing can be used, such as for FDMA, TDMA, or CDMA. The present invention is particularly useful for CDMA applications, but is not so limited.

The base band processor 430 also performs the additional function of determining when antenna diversity is justified in light of the additional power consumption thereof.

Figure 5 shows the general program flow of a control section of a base  
5 band processing. This control section provides the control signal to the second RF processor 422. Figure 5 is to be taken as an exemplary flow chart. Naturally, other program flows can be implemented without departing from the spirit and scope of the present invention.

A first step 510, a radio frequency signal is received in the first antenna  
10 410. It is input for processing in the first RF processor 420 in the second step 512 which, among other processes, converts the radio frequency signal to a base band signal. At step 514, the base band processor 430 checks to determine whether diversity is on. If diversity is on, then the RF signal received on the second antenna is processed in the second processor 422 at step 516. The signal  
15 processed in the second processor 422 is then demodulated and the two processed signals are combined in the base band processor 430 at step 518. If at step 514 it is determined that diversity is off, then the signal from the first processor 420 is demodulated at step 517 for further processing in other circuit elements, such as a digital signal processor (DSP). Further processing will be necessary for such  
20 implementations as CDMA, TDMA and FDMA systems to convert the base band signal into a voice signal or data signal, as the situation makes appropriate. The two branches of the process then combine and at step 520 the base band processor 430 determines whether diversity should be on.

This determination as to whether the performance gain of the intended  
25 diversity justifies the extra power consumption can employ a number of different mechanisms. The determination can be made at the mobile station or the mobile station can send information about the quality of the link to the base station. If the

base station judges that the quality of the link is sufficiently good and also has spare capacity then it allows diversity to be switched off in the mobile station.

There are two general types of post detection selection diversity receivers available. In the first type, the selection of one of the received signals is  
5 dependent upon the received signal strength (RSS) of the signals. This type of diversity receiver is known as the level comparison diversity technique. The selection of the second type is dependent upon the phase error estimates. This type of post detection selection diversity receiver is known as a phase likelihood comparison technique, as more fully explained in WO 93/06668 herein  
10 incorporated by reference. Diversity is then turned on or off based on this determination, and the process returns to the initial step 510.

In the level comparison diversity technique, the RSS of each receive signal is detected and compared to others. The received signal having the RSS is selected or used by the radio telephone. This simple system is relatively effective  
15 in signal fading environment and is a superior system having a single antenna receiver. However, the level of comparison diversity technique does not offer any advantage over a single antenna system in a static environment. The phase likelihood comparison technique utilizes a phase error estimate for each of the received signals, selecting the signal with the smallest estimated phase error.

20 Other systems can be employed, such as the TDMA system wherein a prediction or signal quality is carried out according to the receive signal level of the two antennas and the slope of these signals from each antenna just before the assigned time slot in the TDMA system.

Another mechanism is to measure the signal to interference ratio (SIR), or  
25 estimate a bit error rate (BER) or frame error rate (FER), or keep track of the number of re-transmissions in cases where the radio link protocol uses re-transmissions, at the antennas in the base band processor 430 to determine which is appropriate.

As mentioned above, if diversity is being used, then the signals from the first and second antennas 410 and 412, as processed in the first and second RF processors 420 and 422, are combined. Combining signals of different antennas by an intermediate frequency gain combination technique, where the detection  
5 frequency signals for the radio frequency parts are phased with each other and summed as known from WO 95/11552 herein incorporated by reference. Phasing takes place by adjusting the frequency phase of the output signal of the local oscillator to the second receiver branch. In practical application, this is often done by processing the two signals separately and forming channel estimates for them  
10 separately. By then, using the individual channel estimates for the two signals, one will adjust for the other the difference (e.g., phase) in the channel and then add the data. The data is often added together using different weights depending on the quality of the two respective signals.

As the signals are summed coherently, noise is incoherently combined and  
15 the signal to noise ratio improves in the diversity receiver. The combined signals are then output to other circuitry for further processing to ultimately result in a voice or data signal.

If diversity is not needed, then the second RF processor 422 is not used. When not using diversity, the mobile station generally needs a higher SIR at the  
20 antenna to get the same performance as when using diversity. Most modern cellular systems include a power control in the forward link. The mobile system will ask the base station to increase its transmit power until the required SIR is reached. Whether this request is granted or not depends on the current load of the system. There will situations when the power cannot be increased and the mobile  
25 stations may be forced into renegotiating currently used services, such as data rates, channel coding, etc. in order to handle the reduced SIR when switching off the diversity processing. Alternatively, the mobile station can be forced to continue diversity processing at the increased power consumption.

In addition or as an alternative to local control, the criteria for when to use a diversity branch can be global. In the global control criteria, the network evaluates the load in different cells and signals to the mobiles when they are allowed to switch off diversity processing. As illustrated in Figure 6, at step 610, a network determines the loads on various cells in a cellular system. If the load of a cell is determined to be light at step 620, there is excess capacity. This means that some of the capacity can be exploited to make some mobile stations perform well without diversity, such as by raising the base station output power for these links at step 630. Then, at step 630, the network signals the mobile stations that they are allowed to switch off diversity processing in some of the less congested cells. While some of the performance is lost when diversity is turned off, it can be compensated for by increasing the transmit power in the forward link to the mobile station to reach a target SIR in one loop and possibly adjust the target SIR based on perceived quality in an outer loop. This can be done by having the mobile station inform the base station that it has switched off diversity, thus triggering an increase in base station output power. Alternatively, the base station power can be ramped up or down after instructing a mobile station to switch off diversity until the output is again at the performance requirement of the transmission. More specifically, a mobile station that operates with diversity needs, on average, less Signal to Interference Ratio (SIR) to decode a received signal with a good result than a mobile station that operates with one antenna. The mobile normally has an internal target SIR to which it aims to operate. This target SIR reflects a signal quality needed to sufficiently decode the incoming signal. There is a power control loop between the mobile and the base station and if the mobile experiences lower SIR than the target value, it will request the base station to increase the base station output power; and if the SIR is higher than the target, it will request the base station to decrease its output power. There is also a slower outer loop that checks the final quality of the decoded signal; and if the

final quality of the decoded signal is too good/bad; the target SIR will be updated accordingly. The base station may or may not impose restrictions on which target SIR a mobile station may ask for (in order to hinder a mobile from requesting too much base station output power and thus take too much of the total capacity).

5           Given this, the two modes (with and without diversity) will correspond to two different target SIRs. If it is decided in the mobile station to switch off diversity, then it will start by increasing its internal target SIR. This action will lead to power control commands to the base station forcing it to increase its output power so that the SIR experienced at the mobile reaches the new (higher) target  
10   value. This leads to better quality in the demodulated signal (measured as BER, FER, SIR, retransmission rate, etc.). If the demodulated signal is good enough, the mobile station switches off the second antenna. The opposite will happen when diversity is switched on. First, the second antenna is switched on. The resulting decoded signal quality is monitored, then the target SIR is decreased and  
15   accordingly, the base station will lower its output power.

          The global control scheme being described could simply be the system checking how the different cells are loaded and whether the signal to the mobile stations were allowed to use the higher or the lower SIR target (corresponding to diversity on or off). The local mode could be the mobile using any measure to  
20   determine whether or not to try to switch off diversity and see (through different quality measurements) if the base station has increased power according to the new target SIR.

          These two control loops (power control to reach a target SIR, and then an outer loop to adjust target SIR based on perceived quality) are how the WCDMA  
25   3GPP standard will operate.

          As shown in step 640, the system then determines whether reevaluation is appropriate and, if it is, returns to step 610.

Thus, Figure 5 illustrates local control in the mobile station for deciding when it is appropriate to use diversity, and Figure 6 shows the flow of when the network is to decide to use diversity in mobile stations. Naturally, it is possible to use both the local control and the network control, global control at the same time.

040070-244



Claims:

1. A mobile station comprising:
  - a first antenna;
  - a first radio frequency processing circuit receiving and processing signals  
5 from said first antenna;
  - a second antenna;
  - a second radio frequency processing circuit receiving and processing  
signals from second antenna; and
  - a base band processing circuit receiving processed radio frequency signals  
10 from said first radio frequency processing circuit and from said second radio  
frequency processing circuit for diversity, and providing a control signal to said  
second radio frequency processing circuit to selectively activate and deactivate  
said second radio frequency processing circuit based on a determination as to  
whether diversity is appropriate.
- 15 2. A mobile station in accordance with claim 1 wherein said first radio  
frequency processing circuit also transmits signals from said mobile station.
3. A mobile station in accordance with claim 1 wherein said control  
signal generated by said base band processing circuit is controlled by a control  
signal from a base station with which said mobile station is in communication.
- 20 4. A mobile station in accordance with claim 3 wherein the base  
station will increase or decrease its output power to said mobile station after  
transmitting said control signal until a sufficient signal quality of the  
communication link.

5. A mobile station in accordance with claim 1 wherein said mobile station informs a base station of its deactivation of diversity so that the base station will adjust its output power until a sufficient signal quality is achieved in accordance with the non-diversity mode.

5 6. A mobile station in accordance with claim 1 wherein said determination as to whether diversity is appropriate is based on a signal quality of a demodulated signal.

7. A mobile station in accordance with claim 1 wherein said determination as to whether diversity is appropriate is based on a level comparison diversity technique.

10

8. A mobile station in accordance with claim 1 wherein said determination as to whether diversity is appropriate is based on a likelihood comparison technique.

9. A mobile station in accordance with claim 1 wherein said determination as to whether diversity is appropriate is based on a measure of bit error rate of a demodulated signal.

15

10. A mobile station in accordance with claim 1 wherein said determination as to whether diversity is appropriate is based on a measure of frame error rate of a demodulated signal.

20 11. A mobile station in accordance with claim 1 wherein said determination as to whether diversity is appropriate is based on a measure of a signal to interference ratio of a demodulated signal.

12. A mobile station in accordance with claim 1 wherein said determination as to whether diversity is appropriate is based on a measure of the number of re-transmissions required.

5 13. A method of controlling diversity in a mobile station, comprising:  
receiving a radio signal on a first antenna;  
processing radio signals from said first antenna in a first radio frequency processing circuit;  
receiving radio signals in a second antenna;  
processing radio signals from the first antenna in a second radio frequency  
10 processing circuit;  
receiving processed radio frequency signals from said first radio frequency processing circuit and from said second radio frequency processing circuit for diversity in a base band processing circuit;  
determining whether diversity is appropriate; and  
15 providing a control signal to said second radio frequency processing circuit to selectively activate and deactivate said second radio frequency processing circuit based on said determination as to whether diversity is appropriate.

14. A method in accordance with claim 13 further comprising  
controlling the generation by said base band processing circuit of said control  
20 signal by a control signal from a base station with which said mobile station is in communication.

15. A method in accordance with claim 14 further comprising adjusting an output power of the base station to said mobile station after transmitting said control signal until a sufficient signal quality of the communication link.

16. A method in accordance with claim 13 further comprising said mobile station informing a base station of its deactivation of diversity so that the base station will adjust its output power until a sufficient signal quality is achieved in accordance with the non-diversity mode.

5 17. A method in accordance with claim 13 wherein said determination as to whether diversity is appropriate includes measuring a signal quality of a demodulated signal.

10 18. A method in accordance with claim 13 wherein said determination as to whether diversity is appropriate includes employing a level comparison diversity technique.

19. A method in accordance with claim 13 wherein said determination as to whether diversity is appropriate includes employing a likelihood comparison technique.

15 20. A mobile station in accordance with claim 1 wherein said determination as to whether diversity is appropriate is based on a measure of at least one of the group consisting of a bit error rate of a demodulated signal, a frame error rate of a demodulated signal, a signal to interference ratio of a demodulated signal, and the number of re-transmissions required.

A mobile station with a receiver having antenna diversity where the diversity processing is controlled from the base band processing circuit and only turned on when the performance gain justifies extra power consumption. The base  
5 band processing circuit may be instructed by the network that it can cease diversity reception after evaluating cell leads within a system.




Figure 1  
(PRIOR ART)




FIGURE 2  
(PRIOR ART)




FIGURE 3  
(PRIOR ART)





Figure 4








FIGURE 6

# **COMBINED DECLARATION AND POWER OF ATTORNEY FOR UTILITY PATENT APPLICATION**

Attorney's Docket No.  
040070-244

As a below-named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below next to my name;

I BELIEVE I AM THE ORIGINAL, FIRST AND SOLE INVENTOR (if only one name is listed below) OR AN ORIGINAL, FIRST AND JOINT INVENTOR (if more than one name is listed below) OF THE SUBJECT MATTER WHICH IS CLAIMED AND FOR WHICH A PATENT IS SOUGHT ON THE INVENTION ENTITLED:

CONTROLLED ANTENNA DIVERSITY

the specification of which

(check one)

☒ is attached hereto;

☐ was filed on \_\_\_\_\_ as

Application No. \_\_\_\_\_




and was amended on \_\_\_\_\_;  
(if applicable)

I HAVE REVIEWED AND UNDERSTAND THE CONTENTS OF THE ABOVE-IDENTIFIED SPECIFICATION, INCLUDING THE CLAIMS, AS AMENDED BY ANY AMENDMENT REFERRED TO ABOVE;

I ACKNOWLEDGE THE DUTY TO DISCLOSE TO THE OFFICE ALL INFORMATION KNOWN TO ME TO BE MATERIAL TO PATENTABILITY AS DEFINED IN TITLE 37, CODE OF FEDERAL REGULATIONS, Sec. 1.56 (as amended effective March 16, 1992);

I do not know and do not believe the said invention was ever known or used in the United States of America before my or our invention thereof, or patented or described in any printed publication in any country before my or our invention thereof or more than one year prior to said application; that said invention was not in public use or on sale in the United States of America more than one year prior to said application; that said invention has not been patented or made the subject of an inventor's certificate issued before the date of said application in any country foreign to the United States of America on any application filed by me or my legal representatives or assigns more than twelve months prior to said application;

I hereby claim foreign priority benefits under Title 35, United States Code Sec. 119 and/or Sec. 365 of any foreign application(s) for patent or inventor's certificate as indicated below and have also identified below any foreign application for patent or inventor's certificate on this invention having a filing date before that of the application(s) on which priority is claimed:

COMBINED DECLARATION AND POWER OF ATTORNEY		Attorney's Docket No. 040070-244																																								
COUNTRY/INTERNATIONAL	APPLICATION NUMBER	DATE OF FILING (day, month, year)	PRIORITY CLAIMED																																							
			YES_ NO_																																							
			YES_ NO_																																							
<p>I hereby appoint the following attorneys and agent(s) to prosecute said application and to transact all business in the Patent and Trademark Office connected therewith and to file, prosecute and to transact all business in connection with international applications directed to said invention:</p> <table style="width: 100%; border: none;"> <tr> <td style="width: 33%;">William L. Mathis 17,337</td> <td style="width: 33%;">Robert G. Mukai 28,531</td> <td style="width: 33%;">William H. Benz 25,952</td> </tr> <tr> <td>Peter H. Smolka 15,913</td> <td>George A. Hovanec, Jr. 28,223</td> <td>Peter K. Skiff 31,917</td> </tr> <tr> <td>Robert S. Swecker 19,885</td> <td>James A. LaBarre 28,632</td> <td>Richard J. McGrath 29,195</td> </tr> <tr> <td>Platon N. Mandros 22,124</td> <td>E. Joseph Gess 28,510</td> <td>Matthew L. Schneider 32,814</td> </tr> <tr> <td>Benton S. Duffett, Jr. 22,030</td> <td>R. Danny Huntington 27,903</td> <td>Michael G. Savage 32,596</td> </tr> <tr> <td>Joseph R. Magnone 24,239</td> <td>Eric H. Weisblatt 30,505</td> <td>Gerald F. Swiss 30,113</td> </tr> <tr> <td>Norman H. Stepno 22,716</td> <td>James W. Peterson 26,057</td> <td>Michael J. Ure 33,089</td> </tr> <tr> <td>Ronald L. Grudziecki 24,970</td> <td>Teresa Stanek Rea 30,427</td> <td>Charles F. Wieland III 33,096</td> </tr> <tr> <td>Frederick G. Michaud, Jr. 26,003</td> <td>Robert E. Krebs 25,885</td> <td>Bruce T. Wieder 33,815</td> </tr> <tr> <td>Alan E. Kopecki 25,813</td> <td>William C. Rowland 30,888</td> <td>Todd R. Walters 34,040</td> </tr> <tr> <td>Regis E. Slutter 26,999</td> <td>T. Gene Dillahunty 25,423</td> <td> </td> </tr> <tr> <td>Samuel C. Miller, III 27,360</td> <td>Patrick C. Keane 32,858</td> <td> </td> </tr> <tr> <td>Ralph L. Freeland, Jr. 16,110</td> <td>Bruce J. Boggs, Jr. 32,344</td> <td> </td> </tr> </table>				William L. Mathis 17,337	Robert G. Mukai 28,531	William H. Benz 25,952	Peter H. Smolka 15,913	George A. Hovanec, Jr. 28,223	Peter K. Skiff 31,917	Robert S. Swecker 19,885	James A. LaBarre 28,632	Richard J. McGrath 29,195	Platon N. Mandros 22,124	E. Joseph Gess 28,510	Matthew L. Schneider 32,814	Benton S. Duffett, Jr. 22,030	R. Danny Huntington 27,903	Michael G. Savage 32,596	Joseph R. Magnone 24,239	Eric H. Weisblatt 30,505	Gerald F. Swiss 30,113	Norman H. Stepno 22,716	James W. Peterson 26,057	Michael J. Ure 33,089	Ronald L. Grudziecki 24,970	Teresa Stanek Rea 30,427	Charles F. Wieland III 33,096	Frederick G. Michaud, Jr. 26,003	Robert E. Krebs 25,885	Bruce T. Wieder 33,815	Alan E. Kopecki 25,813	William C. Rowland 30,888	Todd R. Walters 34,040	Regis E. Slutter 26,999	T. Gene Dillahunty 25,423		Samuel C. Miller, III 27,360	Patrick C. Keane 32,858		Ralph L. Freeland, Jr. 16,110	Bruce J. Boggs, Jr. 32,344	
William L. Mathis 17,337	Robert G. Mukai 28,531	William H. Benz 25,952																																								
Peter H. Smolka 15,913	George A. Hovanec, Jr. 28,223	Peter K. Skiff 31,917																																								
Robert S. Swecker 19,885	James A. LaBarre 28,632	Richard J. McGrath 29,195																																								
Platon N. Mandros 22,124	E. Joseph Gess 28,510	Matthew L. Schneider 32,814																																								
Benton S. Duffett, Jr. 22,030	R. Danny Huntington 27,903	Michael G. Savage 32,596																																								
Joseph R. Magnone 24,239	Eric H. Weisblatt 30,505	Gerald F. Swiss 30,113																																								
Norman H. Stepno 22,716	James W. Peterson 26,057	Michael J. Ure 33,089																																								
Ronald L. Grudziecki 24,970	Teresa Stanek Rea 30,427	Charles F. Wieland III 33,096																																								
Frederick G. Michaud, Jr. 26,003	Robert E. Krebs 25,885	Bruce T. Wieder 33,815																																								
Alan E. Kopecki 25,813	William C. Rowland 30,888	Todd R. Walters 34,040																																								
Regis E. Slutter 26,999	T. Gene Dillahunty 25,423																																									
Samuel C. Miller, III 27,360	Patrick C. Keane 32,858																																									
Ralph L. Freeland, Jr. 16,110	Bruce J. Boggs, Jr. 32,344																																									
and: _____																																										
<p>Address all correspondence to: Ronald L. Grudziecki BURNS, DOANE, SWECKER &amp; MATHIS, L.L.P. P.O. Box 1404 Alexandria, Virginia 22313-1404</p>																																										
<p>Address all telephone calls to: <u>Charles F. Wieland III</u> at (703) 836-6620.</p>																																										
<p>I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.</p>																																										
FULL NAME OF SOLE OR FIRST INVENTOR		SIGNATURE	DATE																																							
Kjell GUSTAFSSON			990701																																							
RESIDENCE		CITIZENSHIP																																								
Borgaslingen 2, SE-224 72 Lund, Sweden		Sweden																																								
POST OFFICE ADDRESS																																										
Borgaslingen 2, SE-224 72 Lund, Sweden																																										
FULL NAME OF SECOND JOINT INVENTOR, IF ANY		SIGNATURE	DATE																																							
Torsten CARLSSON			990701																																							
RESIDENCE		CITIZENSHIP																																								
Viborgsslingen 46, SE-224 72 Lund, Sweden		Swedish																																								
POST OFFICE ADDRESS																																										
Viborgsslingen 46, SE-224 72 Lund, Sweden																																										
FULL NAME OF THIRD JOINT INVENTOR, IF ANY		SIGNATURE	DATE																																							
Torgny PALENIUS			990701																																							
RESIDENCE		CITIZENSHIP																																								
Svalortsvagen 10, SE-246 50 Lund, Sweden		Swedish																																								
POST OFFICE ADDRESS																																										
Svalortsvagen 10, SE-246 50 Lund, Sweden																																										